

Electrical Safety – **Construction**

Relocatable dwellings >

This Information Bulletin has been developed to assist electrical contractors, electrical workers, owners and operators of relocatable dwellings in understanding the electrical safety issues associated with the transport and connection to low voltage electricity supply of such structures to sites in the Northern Territory.

This bulletin applies to:

- > Aboriginal Communities;
- > Mine Sites;
- > Domestic Installations;
- > Commercial Installations; and
- > Temporary Installations including work camps and construction sites.

**Legislation**

Under Clause 67 and 68 of the *Electricity Reform Act* (Northern Territory) the Owner or Operator of the relocatable dwelling and their Electrical Contractor have a responsibility to ensure the relocatable dwelling complies with AS/NZS 3000:2007 Wiring Rules prior to connection to a low voltage power source.

**Relocatable dwellings manufactured in Queensland may not be compliant with AS/NZS 3000:2007 Wiring Rules.**

If the relocatable dwellings are intended to be relocated frequently and are connected via a plug and socket then compliance with AS/NZS 3001:2008 Electrical installations—Transportable Structures and Vehicles Including Their Site Supplies is mandatory.

If the relocatable dwellings are intended to be used on construction sites then compliance with AS/NZS 3012:2003 Electrical installations—Construction and demolition sites is also mandatory.

The manufacturers Electrical Safety Certificate or similar issued at the time of construction cannot be relied upon once the relocatable dwelling has been transported to site, as damage may have occurred during transportation.

It is vital that the Electrical Contractor who connects the relocatable dwelling to a low voltage electricity supply carry out a full inspection of the dwelling as per Section 8 of AS/NZS 3000:2007 Wiring Rules, which includes removing socket outlets and light switches to ensure that the accessory type and installation methods comply with standards.

putting safety first >



A Certificate of Compliance must be submitted which accounts for the entire installation.
i.e. Relocatable dwelling manufactured by XYZ Corporation was tested for compliance with AS/NZS 3000:2007 Wiring Rules following transportation to site, and found to be compliant.

Refer to Regulation 5 Electricity Reform (Safety and Technical) Regulations for the correct procedure for the issuing of Certificates of Compliance in the Northern Territory.

Definitions

Low Voltage is defined by AS/NZS 3000:2007 Wiring Rules as:

- > 50 < 1000 Volts AC, or
- > 120 < 1500 Volts ripple free DC

A low voltage electricity supply is defined as:

- > Mains supply from a supply authority.
- > Generator supply, either site power generation or portable generator.
- > Inverter Supply from a solar photovoltaic / storage battery system.
- > Other alternative energy sources, including wind power, fuel cells, etc.

If you have any doubts about the quality of the electrical installation or connection methods of relocatable dwellings and would like to make a complaint or verify that your intended actions will be correct, please do not hesitate to contact the NT WorkSafe – Electrical Safety Work Unit.

NT WorkSafe >

GPO Box 1722

Darwin NT 0801

Website: www.worksafe.nt.gov.au

Telephone: 1800 019 115

Facsimile: (08) 8999 5141

Email: ntworksafe@nt.gov.au